

Detect AC voltage

Product features

- non-contact detection of AC voltage from 90 V AC to 1000 V AC
- rugged, double molded case
- suitable for outlets or against wire insulation testing
- flashing red LED light indicator
- audible beeper indicator
- built-in bright flashlight with ON/OFF button
- convenient size with pocket clip
- for use on 50/60 Hz circuits
- supply by 2 x 1.5 V batteries (LR03)



 **IP54**

CAT III

1000 V

Application

The Non-contact AC Voltage Tester is easy to use – just touch the tip to a terminal strip, outlet, or supply cord. When the tip glows red and the unit beeps, you know there’s voltage present. Electricians, maintenance, service and safety personnel or homeowners can quickly test for energized circuits in the workplace or at home.

Technical specification

indicators	LED and audible beeper	
voltage range	90...1000 V AC (50/60 Hz)	
overvoltage category	III 1000 V	
ingress protection	IP54	
operating temperature	-10...+50°C 14...122°F	
humidity	80% without condensation	
battery	2 x 1.5 V battery (AAA, NEDA 24A or IEC LR 03)	
dimensions	length	177 mm 7.0"
	diameter	27 mm 1.1"
tester weight (without batteries)	100 g 0.2 lbs	
flashlight	one white LED	

